

# MAZDA

## TRANSISTORS A JONCTION PNP TABLEAU D'EQUIVALENCE

Marques	Mélangeur et Oscillateur		Amplificateur M. F.	Préamplificateur B. F. et driver	Amplificateur B. F.
	Types	de coup.			
C S F .....	SFT108	10 MHz	SFT106 - SFT107	SFT101 - SFT102 SFT105	SFT121 - SFT122 SFT123
BELVU .....					
PHILIPS .....	OC44	15 MHz	OC45	OC70 - OC71	OC72
R. T. ....	>	>	>	>	>
MULLARD .....	>	>	>	>	>
AZDAM .....	>	>	>	>	>
EDISWAN .....	XA102	8 MHz	XA101	XB102 - XB103 - XB104	XC101
R. C. A. ....	2N140	7 MHz	2N139 - 2N169	2N77 - 2N104	2N109 - 2N270
	2N219	7 MHz	2N218 - 2N409	2N105 - 2N109	2N407 - 2N408
	2N247	30 MHz		2N175 - 2N405	
	2N411	16,5 MHz		2N406	
	2N412	16,5 MHz			
GEco .....	2N123	8 MHz	2N135 - 2N136	2N43 - 2N265	2N186 - 2N186A
	2N136	6,5 MHz		2N189 - 2N190	2N187 - 2N187A
	2N137	10 MHz		2N191 - 2N192	2N188 - 2N188A
G. T. ....	GT761R		GT759R - GT760R - GT760	GT81 - GT81R	GT109
RAYTHEON .....	2N114	20 MHz	2N112 - 2N113	2N65 - 2N132	2N138
	CK766 - 2N271	10 MHz	CK760	2N362 - 2N363	2N138A
	2N415	10 MHz	2N413 - 2N414	CK722 - CK725	
	2N417	20 MHz	- 2N416	2N427 - 2N428	
TEXAS .....	2N252	7 MHz	234	2N238 - 310 - 350 351 - 352	2N185 355 - 2N250 2N251
	235				
	2N308 - 2N309	30 MHz			
C B S .....				2N180 - 2N256 HA8 - HA9	2N181 - 2N255 HD197
PHILCO .....				2N207 - 2N207A 2N207B	2N223 à 2N227
SYLVANIA .....				2N34	2N141 - 2N143
INTERMETAL .....	OC410	7 MHz	OC390	OC340	OC38
SIEMENS .....				T65	TF75 - TF77
TEKADE .....	GFT44		GFT45	GFT20 - GFT21	GFT32
TELEFUNKEN .....	OC613		OC612	OC601 - OC602	OC604
<b>Types MAZDA Equivalents :</b>					
MAZDA .....	37T1 - 31T1	10 MHz	35T1 - 36T1	965T1 - 989T1	941T1 - 986T1
CFTH .....	36T1 - 32T1	6,5 MHz	33T1 - 34T1	990T1 - 991T1 - 992T1	987T1 - 988T1